# **Driver Transistors**

# **NPN Silicon**

#### **Features**

• These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

## **MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Collector – Emitter Voltage  MMBTA05LT1  MMBTA06LT1	V <sub>CEO</sub>	60 80	Vdc
Collector - Base Voltage  MMBTA05LT1  MMBTA06LT1	V <sub>CBO</sub>	60 80	Vdc
Emitter – Base Voltage	V <sub>EBO</sub>	4.0	Vdc
Collector Current – Continuous	Ic	500	mAdc

# THERMAL CHARACTERISTICS

Characteristic	Symbol	Max	Unit
Total Device Dissipation FR-5 Board (Note 1) T <sub>A</sub> = 25°C Derate above 25°C	P <sub>D</sub>	225 1.8	mW mW/°C
Thermal Resistance, Junction-to-Ambient	$R_{ heta JA}$	556	°C/W
Total Device Dissipation Alumina Substrate, (Note 2) T <sub>A</sub> = 25°C Derate above 25°C	P <sub>D</sub>	300 2.4	mW mW/°C
Thermal Resistance, Junction-to-Ambient	$R_{\theta JA}$	417	°C/W
Junction and Storage Temperature	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C


Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

- 1. FR-5 = 1.0  $\times$  0.75  $\times$  0.062 in.
- 2. Alumina = 0.4  $\times$  0.3  $\times$  0.024 in. 99.5% alumina.



# ON Semiconductor®

## http://onsemi.com





SOT-23 CASE 318 STYLE 6

#### MARKING DIAGRAMS





MMBTA05LT1

MMBTA06LT1

1H, 1GM = Specific Device Code

M = Date Code\* ■ Pb-Free Package

(Note: Microdot may be in either location)

\*Date Code orientation and/or overbar may vary depending upon manufacturing location.

# **ORDERING INFORMATION**

See detailed ordering and shipping information in the package dimensions section on page 4 of this data sheet.


1

# **ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C unless otherwise noted)

Characteristic		Symbol	Min	Max	Unit
OFF CHARACTERISTICS		1			
Collector – Emitter Breakdown Voltage (Note 3) $(I_C = 1.0 \text{ mAdc}, I_B = 0)$	MMBTA05 MMBTA06	V <sub>(BR)CEO</sub>	60 80	_ _	Vdc
Emitter – Base Breakdown Voltage ( $I_E = 100 \mu Adc, I_C = 0$ )		V <sub>(BR)EBO</sub>	4.0	-	Vdc
Collector Cutoff Current (V <sub>CE</sub> = 60 Vdc, I <sub>B</sub> = 0)		I <sub>CES</sub>	-	0.1	μAdc
Collector Cutoff Current $(V_{CB} = 60 \text{ Vdc}, I_E = 0)$ $(V_{CB} = 80 \text{ Vdc}, I_E = 0)$	MMBTA05 MMBTA06	Ісво	- -	0.1 0.1	μAdc
ON CHARACTERISTICS					
DC Current Gain $ (I_C = 10 \text{ mAdc}, V_{CE} = 1.0 \text{ Vdc}) $ $ (I_C = 100 \text{ mAdc}, V_{CE} = 1.0 \text{ Vdc}) $		h <sub>FE</sub>	100 100	- -	-
Collector – Emitter Saturation Voltage (I <sub>C</sub> = 100 mAdc, I <sub>B</sub> = 10 mAdc)		V <sub>CE(sat)</sub>	-	0.25	Vdc
Base – Emitter On Voltage (I <sub>C</sub> = 100 mAdc, V <sub>CE</sub> = 1.0 Vdc)		V <sub>BE(on)</sub>	-	1.2	Vdc
SMALL-SIGNAL CHARACTERISTICS				•	٠
Current – Gain – Bandwidth Product (Note 4) $(I_C = 10 \text{ mA}, V_{CE} = 2.0 \text{ V}, f = 100 \text{ MHz})$		f⊤	100	_	MHz

<sup>3.</sup> Pulse Test: Pulse Width  $\leq$  300  $\mu$ s, Duty Cycle  $\leq$  2.0%.

<sup>4.</sup> f<sub>T</sub> is defined as the frequency at which |h<sub>fe</sub>| extrapolates to unity.



<sup>\*</sup>Total Shunt Capacitance of Test Jig and Connectors For PNP Test Circuits, Reverse All Voltage Polarities

Figure 1. Switching Time Test Circuits




Figure 2. Current-Gain — Bandwidth Product




Figure 3. Capacitance




Figure 4. Switching Time




Figure 5. DC Current Gain




Figure 6. Collector Emitter Saturation Voltage vs. Collector Current




Figure 7. Base Emitter Saturation Voltage vs.
Collector Current




Figure 8. Base Emitter Voltage vs. Collector Current




Figure 9. Collector Saturation Region




Figure 10. Base–Emitter Temperature Coefficient




Figure 11. Safe Operating Area


## **ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
MMBTA05LT1G	SOT-23 (Pb-Free)	3000 / Tape & Reel
MMBTA05LT3G	SOT-23 (Pb-Free)	10,000 / Tape & Reel
MMBTA06LT1G	SOT-23 (Pb-Free)	3000 / Tape & Reel
MMBTA06LT3G	SOT-23 (Pb-Free)	10,000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

## PACKAGE DIMENSIONS

SOT-23 (TO-236) CASE 318-08 **ISSUE AN** 



## NOTES

- 1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982. 2. CONTROLLING DIMENSION: INCH.
- MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL. 318-01 THRU -07 AND -09 OBSOLETE, NEW STANDARD


	MILLIMETERS			INCHES		
DIM	MIN	NOM	MAX	MIN	NOM	MAX
Α	0.89	1.00	1.11	0.035	0.040	0.044
A1	0.01	0.06	0.10	0.001	0.002	0.004
b	0.37	0.44	0.50	0.015	0.018	0.020
С	0.09	0.13	0.18	0.003	0.005	0.007
D	2.80	2.90	3.04	0.110	0.114	0.120
E	1.20	1.30	1.40	0.047	0.051	0.055
е	1.78	1.90	2.04	0.070	0.075	0.081
L	0.10	0.20	0.30	0.004	0.008	0.012
L1	0.35	0.54	0.69	0.014	0.021	0.029
HE	2 10	2 40	2 64	0.083	0.094	0.104

#### STYLE 6:

PIN 1. BASE

- **EMITTER** 2.
- COLLECTOR

## **SOLDERING FOOTPRINT\***



\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and un are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice on semiconductor and are registered readerlands of semiconduction Components industries, ILC (SCILLC). SciLLC reserves are right to finate changes without further holice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifically oxyr over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free USA/Canada

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center

Phone: 81-3-5773-3850

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative